

Aura LED Opti T8 HF G3, Compatibility list
Aura LED Opti T8 HF G3 - 600mm 7,5W

Brand	ECG Model	Channel
B.A.G	BSC18.1FX-11/220-240	1 x 18W
Helvar	EL1X18ngn	1 x 18W
OSRAM	OTP-OPTIMAL 1x18-40	1 x 18W
OSRAM	QT-FIT 5/8 1x18-39	1 x 18W
OSRAM	QT-FIT8 1x18	1 x 18W
OSRAM	QTP8 1X18	1 x 18W
Philips	HF-P 118 TLD EII 220-240	1 x 18W
Philips	HF-P 118 TL-D III IDC	1 x 18W
Philips	HF-P 118/136 TL-D III	1 x 18W
Philips	HF-S 118 TL-D II	1 x 18W
Philips	HF-S 118/136 TL-D II	1 x 18W
Tridonic	PC 1X18 T8 PRO IP	1 x 18W
Tridonic	PC 1X18 T8 TOP SI	1 x 18W
Tridonic	PC 1X18-24W BASIC SI	1 x 18W
Vossloh	ELXc 136.200	1 x 18W
Helvar	EL2x18s	2 x 18W
HEP	ESB 218-40	2 x 18W
OSRAM	QT Fit 5/8 2x18-39	2 x 18W
OSRAM	QT-FIT8 2x18	2 x 18W
OSRAM	QTP8 2x18	2 x 18W
OSRAM	QTP-OPTIMAL 2x18-40	2 x 18W
Philips	HF-P 218 TLD EII 220-240	2 x 18W
Philips	HF-P 218 TL-D III IDC	2 x 18W
Philips	HF-P 218/236 TL-D III	2 x 18W
Philips	HF-S 218 TL-D II	2 x 18W
Philips	HF-S 218/236 TL-D II	2 x 18W
Tridonic	PC 2X18 T8 PRO IP	2 x 18W
Tridonic	PC 2X18 T8 TEC	2 x 18W
Tridonic	PC 2X18 T8 TOP SI	2 x 18W
Vossloh	ELXc 236.217	2 x 18W
B.A.G	BCS18.3-4LR-01/220-240	3 x 18W
Helvar	EL 3/4X18ngn	3 x 18W
OSRAM	QT-FIT8 3X18 4X18	3 x 18W
OSRAM	QTP8 3x18,4X18	3 x 18W
Philips	HF-P 3/4 18 TLD EII 220-240	3 x 18W
Philips	HF-P 3/4 18 TL-D III IDC	3 x 18W
Philips	HF-S 3/418 TL-D II	3 x 18W
Tridonic	PC 3/4X18 T8 PRO IP	3 x 18W
Tridonic	PC 3/4X18 T8 TOP IP	3 x 18W
B.A.G	BCS18.3-4LR-01/220-240	4 x 18W
Helvar	EL 4X18ngn	4 x 18W
OSRAM	QT-FIT8 3X18 4X18	4 x 18W
OSRAM	QTP8 3x18,4X18	4 x 18W
Philips	HF-P 3/4 18 TLD EII 220-240	4 x 18W
Philips	HF-P 3/4 18 TL-D III IDC	4 x 18W
Philips	HF-S 3/418 TL-D II	4 x 18W
Tridonic	PC 3/4X18 T8 PRO IP	4 x 18W
Tridonic	PC 3/4X18 T8 TOP IP	4 x 18W

Aura LED Opti T8 HF G3 - 1200mm 15W

Brand	ECG Model	Channel	Comment
B.A.G	BCS36.1FX-11/220-240	1 x 36W	
B.A.G	D58.1-2302E	1 x 36W	
Helvar	EL 1x36/40/18s	1 x 36W	
Helvar	EL 1X36ngn	1 x 36W	
OSRAM	QT-Fit 5/8 1x18-39	1 x 36W	
OSRAM	QT-Fit 8 1x36	1 x 36W	
OSRAM	QTP8 1x36	1 x 36W	
OSRAM	QTP-OPTIMAL 1x18-40	1 x 36W	
Philips	HF-B 136 TLD EII 220-240	1 x 36W	
Philips	HF-B 136/236 TLD EII 220-240	1 x 36W	
Philips	HF-P 118/136 TL-D III	1 x 36W	
Philips	HF-P 136 PLL 220-240	1 x 36W	
Philips	HF-P 136 TL-D III IDC	1 x 36W	
Philips	HF-R 136 PLL 220-240	1 x 36W	Dim ok
Philips	HF-R 136 PL-L EII	1 x 36W	Dim ok
Philips	HF-S 118/136 TL-D II	1 x 36W	
Philips	HF-S 136 TL-D II	1 x 36W	
Tridonic	PC 1/30 T8 PRO	1 x 36W	
Tridonic	PC 1/36 TCL PRO	1 x 36W	
Tridonic	PC 1X36 T8 PRO IP	1 x 36W	
Vossloh	Type ELXc 136.200	1 x 36W	
Vossloh	Type Elxc 136.207	1 x 36W	
OSRAM	QTP8 2x36	2 x 36W	
OSRAM	QT-FIT8 2x36	2 x 36W	
OSRAM	QT Fit 5/8 2x18-39	2 x 36W	
OSRAM	QTP-OPTIMAL 2x18-40	2 x 36W	
Philips	HF-P 236 TL-D III IDC	2 x 36W	
Philips	HF-R 236 TLD EII	2 x 36W	Dim ok
Philips	HF-P 218/236 TL-D III	2 x 36W	
Philips	HF-S 218/236 TL-D II	2 x 36W	
Philips	HF-B 136/236 TLD EII 220-240	2 x 36W	
Philips	HF-P 236 TLD EII 220-240	2 x 36W	
Helvar	EL 2X36/40S	2 x 36W	
Tridonic	PC 2/36 TCL PRO	2 x 36W	
Tridonic	PC2X36 T8 TOP SI	2 x 36W	
Tridonic	PC 2/36 T8 INDVSTRY	2 x 36W	
Vossloh	ELXc 263.208	2 x 36W	
Vossloh	ELXc 236.202	2 x 36W	
Vossloh	ELXc 336.214	3 x 36W	

Aura LED Opti T8 HF G3 - 1500mm 23W

Brand	ECG Model	Channel	Comment
ABB	EVG 1X58 CF	1 x 58W	
B.A.G	BCS 58.1FX-11/220-240	1 x 58W	
B.A.G	BCS58.1SR-01/220-240	1 x 58W	
B.A.G	D58.1-2302E	1 x 58W	
Helvar	EL1x58HF	1 x 58W	
OSRAM	QT-FIT8 1X58-70	1 x 58W	
OSRAM	QTP 1X58/230-240	1 x 58W	
OSRAM	QTP8 1X58	1 x 58W	Dim ok
OSRAM	QTP-OPTIMAL 1X54-58	1 x 58W	
Philips	HF-B 158 TLD 220-240	1 x 58W	
Philips	HF-B 158 TLD EII 220-240	1 x 58W	
Philips	HF-E 1/2 58 TL-D II	1 x 58W	
Philips	HF-P 158 TLD EII 220-240	1 x 58W	
Philips	HF-P 158 TL-D III IDC	1 x 58W	
Philips	HF-R 158 TLD EII	1 x 58W	Dim ok
Philips	HF-S 158 TL-D II	1 x 58W	
Tridonic	PC 1X58 T8 PRO IP	1 x 58W	
Tridonic	PC 1X58 T8 TOP SI	1 x 58W	
Vossloh	ELXc 158.201	1 x 58W	
Vossloh	ELXc 158.218	1 x 58W	
OSRAM	QT-FIT 5/8 2X54-58	2 x 58W	
OSRAM	QTP-OPTIMAL 2X54-58	2 x 58W	
OSRAM	QT-FIT8 2X58-70	2 x 58W	
OSRAM	QT-FIT8 2X58	2 x 58W	
Philips	HF-P 258 TLD EII 220-240	2 x 58W	
Philips	HF-S 258 TL-D II	2 x 58W	Dim ok
Philips	HF-R 258 TLD EII	2 x 58W	
Tridonic	PC 2X58 T8 TOP SI	2 x 58W	
Tridonic	PC 2/58 T8 PRO	2 x 58W	
Tridonic	PC 2/58 T8 INDUSTRY	2 x 58W	
BAG	SCS58.2SR-11/220-240	2 x 58W	
BAG	BCS58.2FX-11/220-240	2 x 58W	
BAG	D58.2-23021E	2 x 58W	
ABB	EVG 2X58 CF ABB	2 x 58W	
Vossloh	Elxc 258.219	2 x 58W	
Vossloh	Elxc 258.203	2 x 58W	

Important notice for Aura LED Opti T8 HF G3!

Before installation, compatibility with the ballast to be used must be determined by using this compatibility list. Ballasts not listed are not approved for operation with Aura LED Opti T8 HF G3. Listed ballasts which are older than 7 years or already have more than 50 000 hours of operation should be replaced before installation of Aura LED Opti T8 HF G3. Please read the instruction manual before installation!